

*If you are using a printed copy of this procedure, and not the on-screen version, then you **MUST** make sure the dates at the bottom of the printed copy and the on-screen version match.
The on-screen version of the Collider-Accelerator Department Procedure is the Official Version.
Hard copies of all signed, official, C-A Operating Procedures are kept on file in the C-A ESHQ Training Office, Bldg. 911A.*

C-A OPERATIONS PROCEDURES MANUAL

3.24 Procedures to be Implemented for Facility Fire Detection and Suppression System Problems and Failures

Text Pages 2 through 8

Attachments

Hand Processed Changes

<u>HPC No.</u>	<u>Date</u>	<u>Page Nos.</u>	<u>Initials</u>
_____	_____	_____	_____
_____	_____	_____	_____
_____	_____	_____	_____
_____	_____	_____	_____

Approved: *Signature on File* _____
Collider-Accelerator Department Chairman Date

R. Karol

3.24 Procedures to be Implemented for Facility Fire Detection and Suppression System Problems and Failures

1. Purpose

This procedure specifies actions to be taken by C-A personnel during operating or shutdown periods when problems arise with the fire detection and/or suppression system. The issues addressed are:

1.1 Site Fire Alarm Failure

1.1.1 Very infrequently the computer system that connects the building fire alarms to the Fire/Rescue (F/R) Group (Building 599), fails. This prevents fire alarms from being transmitted to F/R so they can respond. If this occurs, F/R will transmit this information to all Building Managers via e-mail/telephone calls/Plectron announcements, and to C-A Management via beepers. Actions to be implemented if this occurs are addressed.

1.2 False Building Fire Alarms

1.2.1 If a false alarm occurs, the F/R Group ensures that it was false and resets the alarms. If the alarm cannot be reset, the MCR Operations Coordinator (OC), during operations, or ESH Coordinator, during shutdown periods, shall only allow bypassing of the alarm under the conditions specified in this procedure.

1.3 Impairment, Partial or Total Failure of a Fire Detection or Suppression System in an Accelerator or Building

1.3.1 The C-A Accelerator Safety Envelopes (ASE), include requirements for the operability of installed fire detection and suppression systems. These requirements include Authorized Alternatives or compensatory actions that may be taken if a system is partially or totally out-of-service. The compensatory actions may be time limited, depending upon the specific ASE requirement. The ASE requirements are translated into C-A OPMs for use by operating personnel. This procedure gives specific guidance on the compensatory measures that are to be implemented while a specific fire detection or suppression system is inoperable.

2. Responsibilities

2.1 The Operations Coordinator (OC) is responsible for implementing this procedure while the MCR is staffed, and for following paragraph 2.3.1 of [C-A OPM 2.2 "Operating Practices"](#) when an Authorized Alternative is used.

- 2.2 The CAS Watch is responsible for implementing this procedure when the MCR is unstaffed, and the CAS Watch is stationed.
- 2.3 If the MCR is unstaffed, and the CAS watch is not stationed, the ESH Coordinator is responsible for implementing this procedure upon notification of the problem.
- 2.4 The advice of the BNL Fire Protection Engineer, Fire Chief or the Fire Captain may be obtained to clarify the requirements of this procedure or assist in their implementation.
- 2.5 BNL Plant Engineering (PE) Fire Alarm Electricians normally respond to Fire Alarm System bypasses, and/or repairs. During non-working hours, this is scheduled through the BNL Site Supervisor. The urgency of the response should be transmitted by MCR directly to the Site Supervisor. C-AD Management shall be informed if any unexpected delays occur. It should be noted that if a Fire Alarm Electrician is not available, any qualified Electrician might perform this work, including a C-AD Electrician under the supervision of an appropriate PE Supervisor.

3. **Prerequisites**

None

4. **Precautions**

- 4.1 The Operational Safety Limits in C-A OPM's [2.5](#), [2.5.1](#), [2.5.2](#) and [2.5.3](#) shall be reviewed to assure that OSL's related to the accelerators and experiments are satisfied.

5. **Procedures**

5.1 **Site Fire Alarm Failure**

- 5.1.1 When notified of a failure in the site fire alarm system such that alarms are not transmitted from C-A facilities to Fire/Rescue, F/R will arrange with C-A staff for scheduled tours of the BNL site as specified by the Fire Captain. C-A watches may monitor facilities or F/R may provide patrols (Reference 7.6) depending upon the availability of personnel. However, C-A is responsible to ensure these patrols take place as required in the remainder of this procedure. Upon receipt of this type of failure, the following actions shall be taken:

5.1.1.1 When neither the MCR nor the CAS Watch are staffed, C-A ESHQ Division shall ensure that the C-A personnel are aware of this condition by sending an e-mail to C-A personnel (see 5.2.2), and informing C-A Management. They shall also contact other staffed C-A Control Rooms to inform them of the problem, and the required response to a building fire alarm as specified in 5.2.2. The ESH Coordinator, or designee, shall provide the F/R Group information on the status of the C-A complex, and discuss the areas where F/R should focus their tours while the site fire alarm system is out of service. Consider staffing the CAS Watch to take the actions specified in 5.2.2.2.

5.1.1.2 If the MCR is staffed, MCR shall take the actions specified in 5.2.1.1.

5.1.1.3 If the MCR is unstaffed, and the CAS Watch is staffed, the CAS Watch shall take the actions specified in 5.2.1.1.

5.1.2 Information below shall be transmitted by personnel as specified in 5.2.1.1, 5.2.1.2 or 5.2.1.3:

5.1.2.1 If a fire alarm system activates in your building, have a person assigned to call the firehouse (911 or 2222), and verify that the Fire/Rescue Group is aware of the alarm. The person should be one that is normally in the facility, such as a receptionist, secretary or facility manager. When a fire alarm goes off, call 2222 or 911 and say: "The fire alarm bells are ringing in Building XXX and I have no further information."

5.1.2.2 If staffed, CAS Watch shall tour the C-A complex at least every 2 hours to determine conditions in remote buildings.

5.1.2.3 When the site fire alarm system is restored, this information shall be transmitted to C-A personnel.

5.2 False Building Fire Alarms

5.2.1 If a false alarm occurs, the F/R Group ensures that it was false and resets the alarms. If the alarm cannot be reset, the MCR Coordinator (when MCR is staffed), or ESH Coordinator (during shutdown periods), shall only allow bypassing of the alarm when all of the following conditions are satisfied:

5.2.1.1 The F/R Group has concluded that the alarm was false.

5.2.1.2 Repairs would take more than 2 hours to accomplish, and there is a valid reason not to wait for the repairs to be completed (e.g., experimental program delay or work delay).

5.2.1.3 The BNL Fire Protection Engineer (or F/R Group Captain), and the Associate Chair for ESHQ, ESHQ Division Head, or ESH Coordinator, agree with the bypass, considering the following in the decision process:

5.2.1.3.1 The requirements of the C-A Complex OSL's including time limits, if applicable, for Authorized Alternatives or compensatory actions (OPM [2.5](#), [2.5.1](#), [2.5.2](#), and [2.5.3](#))

5.2.1.3.2 The risk of equipment loss along with the programmatic impact of not allowing the bypass.

5.2.1.3.3 Compensatory actions, which may include additional remote monitoring of the equipment in the area where the alarm is bypassed, increased walk-through of the affected area (if possible), etc.

5.2.1.3.4 Consider de-energizing equipment in the affected area, and/or prohibiting personnel into the area, while the alarm is bypassed.

5.2.1.4 As soon as practical, the bypassed alarm shall be restored to service. If entry to an area under control of the Access Controls System or the Particle Accelerator Safety System is required for repair, the C-A Maintenance Coordinator shall coordinate with BNL Plant Engineering regarding the earliest time to complete repairs. In all other areas, the Building Manager of the affected building shall coordinate the repair with Plant Engineering.

5.3 Partial or Total Failure of a Fire Detection or Suppression System in a Building or Accelerator

5.3.1 Accelerator Operating and Affected Area Not Accessible due to Beam Operations

5.3.1.1 Check the ASE requirements in the appropriate C-A OPM 2.5 series to see if an Authorized Alternative or compensatory action is specified and obtain the necessary approvals as stated in the procedure. If a time limit for the compensatory action is specified, track this time interval and take the required actions if the fire detection or suppression system is not restored within the specified interval.

5.3.1.2 Specific compensatory actions are as follows:

- 5.3.1.2.1 For Tandem, TTB and Linac - conduct 2-hour tours of the enclosed areas by visually inspecting through gates that allow inspection and by smelling for smoke.
- 5.3.1.2.2 For Switchyard and Target Caves - conduct 2-hour tours of the enclosed areas by visually inspecting through gates that allow inspection and by smelling for smoke. Note that the airflow is normally from the AGS to the switchyard and target caves so this may also detect smoke from the AGS.
- 5.3.1.2.3 For Booster, AGS, ATR and RHIC - conduct 2-hour tours of the enclosed areas by visually inspecting through gates that allow inspection and by smelling for smoke.
- 5.3.1.2.4 For RHIC IRs - conduct 2-hour tours of the enclosed areas by visually inspecting through gates that allow inspection and by smelling for smoke or post a full time Fire Watch who can verbally communicate with BNL F/R by radio or phone as specified in the particular ASE requirement.
- 5.3.1.2.5 All Areas
 - 5.3.1.2.5.1 If any equipment trips twice in an 8-hour period, a third reset is allowed only if the affected equipment is first visually inspected.
 - 5.3.1.2.5.2 A visual inspection is required if magnet currents are abnormal (e.g. fluctuating, pulsing or out of expected range, etc.) or if the beam cannot be controlled as expected.
 - 5.3.1.2.5.3 All high temperature alarms or trips of equipment (windings, cooling water, etc.) shall be visually investigated locally before restoring power to the affected equipment.

5.3.1.3 As soon as practical, the ESH Coordinator, ESHQ Division Head, or ESHQ Chair, shall inform the C-AD BAO Facility Representative of the decision to continue facility operation with an inoperable fire detection, and/or fire suppression, system.

5.3.2 Accelerator Support Buildings During Accelerator Operations

5.3.2.1 A tour of the building shall be conducted every two hours until the fire detection or suppression system is restored to service. If work is being conducted in the building a full time Fire Watch shall be posted as determined by the BNL Fire Protection Engineer, Fire Chief, Fire Captain, ESHQ Associate Chair, ESHQ Division Head or ESH Coordinator.

5.3.2.2 As soon as practical, the ESH Coordinator, ESHQ Division Head, or ESHQ Chair, shall inform the C-AD BAO Facility Representative of the decision to continue facility operation with an inoperable fire detection, and/or fire suppression, system.

5.3.3 Accelerator Shutdown

5.3.3.1 A tour of the building shall be conducted every two hours until the fire detection or suppression system is restored to service. If work is being conducted in the building a full time Fire Watch shall be posted as determined by the BNL Fire Protection Engineer, Fire Chief, Fire Captain, ESHQ Associate Chair, ESHQ Division Head or ESH Coordinator.

5.3.3.2 If the area is a posted High Radiation Area, entry to the area is not needed and tours of the enclosed areas shall be performed by visually inspecting through gates that allow inspection and by smelling for smoke.

6. Documentation

None

7. References

- 7.1 [C-A-OPM 2.5, Operational Safety Limits/Accelerator Safety Envelope For AGS, Booster and Linac.](#)
- 7.2 [C-A-OPM 2.5.1, Accelerator Safety Envelope Parameters for C-A Tandem Van de Graaff.](#)
- 7.3 [C-A-OPM 2.5.2, RHIC Accelerator Safety Envelope Parameters.](#)
- 7.4 [C-A-OPM 2.5.3, BAF Accelerator Safety Envelope Parameters.](#)

7.5 [C-A-OPM 2.2, Operating Practices](#)

7.6 [SBMS ESH Standard 2.4.0.](#)

7.7 [Emergency Services Division Procedure FR-FPR-5.1.4, Compensatory Interim Fire Protection Measures.](#)

8. Attachments

None